4

SPRT TL21 熱感微型印表機網路設定

1. 請取出 TL21 原廠測試標籤樣本,確認標籤樣本中的「IP 位址」。





2. 連接 PC 網路線至印表機。





SPRT TL21 熱感微型印表機網路設定

3. 變更電腦上網路介面卡 IPV4 的 IP 設成與印表機同一網段:192.168.1.xxx(0~225)。 **請記住原本電腦中的 IP 位址**

Z	✓ 信田湾信塚路瑟要 於斷湾信約 太網路內容	<u>自迫 番新会交流信道地</u> ×	檢視這個連線的狀態	變更這個連線的
[路]	功省生			
連	網際網路通訊協定第 4 版 (TCP/IPv4) - 內容	9	×	
1	一般			
這	如果您的網路支援這項功能,您可以取 詢問網路系統管理員正確的 IP 設定。	导自動措派的 IP 設定。否则,	您必須	
	○ 自動取得 IP 位址(O)			
18	使用下列的 IP 位址(S):		_	
8	IP 位址(I):	192.168.1.100		
8	子網路遮置(U):	255 . 255 . 255 . 0		
	預設閘道(D):	192.168.1.1		
	○ 自動取得 DNS 伺服器位址(B)			
	●使用下列的 DNS 伺服器位址(E):		_	
	慣用 DNS 伺服器(P):	168 . 95 . 1 . 1		
-	其他 DNS 伺服器(A):	8.8.4.4		
	□ 結束時確認設定(L)	進階	(V)	

 開啟電腦網頁瀏覽器(以 Google Chrome 為例), 鍵入印表機 IP: 192.168.1.114(同標籤樣本中的 IP 位址), 進入印表機設定網頁。

Printer Setup	x +								v	- 0 X
← → C ▲ 不安全 1	2.168.1.114								19 5	
				1222						
				Welco	ome SPRT Printer	r				
Version Info										
Main Firmware							N-008 1.0	6		
Boot Firmware							Ver 1.00			
Network Info										
Print Port							9100			
WEB Port							80 78 0o 8b	of ft bb		
IP Address							192 168 1	1114		
Netmask							255 255 2	55.0		
Gateway							192 168 1	.1		
Printer Network Setting										
MAC Address							28-0e-88	o-e1-f1-bb		
IP Address							192.168	1.114		
Natmask							255 255	255.0		
Calman							103 102			
Galeway							132.100	1.1		
Setup										
Printer Parameter Setting										
Factory.	SPRT		Model	TL21		Serial Number:	TL21E22020000001	T	cp Keep Time(Second) 300	
Baud Rate:	9600 ¥	Data bit:	8 bit 🗸	Parity:	None 🗸	Handshaking:	RTSICTS V	Language:	Chinese-BIG5 V	
PrintFont:	12*24 ¥	PrintWidth:	30mm 🗸	PrintDensity:	Light ¥	PrintSpeed:	70mm/S ¥	PrintMode	票据>	
BlackMark:	ON ¥	NormalPaperSensor:	1 *	LablePaperSensor	1 💌	PrintDirection:	Reverse 🗸	Command Set	SPMP ¥	
CodePage.	CP437 ¥	PaperOutReprint.	ON ¥	USB Class:	Printer 🕶	DHCP Enable	OFF 🛩			
Setup										
Software Lindate										
Indata										
Opene										



SPRT TL21 熱感微型印表機網路設定

5. 藍色箭頭方框處鍵入「變更」的 IP 位址後,紅色箭頭方框處存檔,即可跳出。

	- 0 >
Welcome SPRT Printer Note show a show	2 x I 2 3
Version Info Note Note Note Note Note Note Note Note	
Main Firmurate N.000.106 Bott Firmurate Wrt 10 Bott Firmurate Wrt 10 Proter Firmurate 9100 MAIN Firmurate 9100 Proter Port 00 MACA Zodesia 9100 PAddess 92.460.114 PAddess 152.463.114 PAddess 92.163.114 Proter Network Ketting 152.163.114 Proter Network Setting 152.163.11 Proter Network Setting 152.163.11 Setter Network Setting 121 Setial	
Bott Finnare Ver 10 Network info 910 Price Port 00 WEB Port 00 MAC Address 02-00-00-01-01-00-00-00-00-00-00-00-00-00-	
Network Info 90 Pint Pot 90 VEB Pin 90 MAC Address 24-9-8-11-8b IP Address 152 168 1.11 4 Pint Poti 152 168 1.11 4 Netmark 152 168 1.11 4 Gateway 192 168 1.11 4 Print Vetwork Setting 192 168 1.11 4 Print Vetwork Setting 192 168 1.11 4 Print Vetwork Setting 192 168 1.11 4 Print Parameter Setting 192 168 1.11 4 Print Parameter Setting 192 168 1.11 4 Setta Parameter Setting 192 168 1.11 4 Parameter Setting 192 168 1.11 4 Setta Parameter Setting 11 1 12 12 20200001 Top Keep Time(Second) Back Rate: 960 v 10 18 18 10 14 Parameter Setting 12 1 12 10 11 11 11 12 10 11 11 12 10 11 11 12 10 11 11 12 10 11 11 12 10 11 11 11 11 11 11 11 11 11 11 11 11	
Pint Print 9100 WE Print 80 MAC Address 92.488.481.14 PAddress 192.180.11.14 Sterray 192.180.11.14 Printer Network Setting Printer Network Setial Number: TL21E202000001 Tcp Keep Time/Second) Printer Network Setial Number: TL21E202000001 Tcp Keep Time/Second) Printer Network Tcp Keep Time/Second) Printer Network Non Printer Network Printer Network Setial Number: TL21E202000001<	
WEB Port 00 MGC Address 260-480-41-bib IP Address 255 255 255 0 Bateray 252 255 255 0 Gateray 192 168 1.114 Printer Network Setting 255 255 255 0 IP Address 192 168 1.114 IP Address IP Address IP Address IP Address IP Address	
M4C Address 28-68-64-11-bb iP Address 152:168.1.14 M4mark 52:255.255.0 Gaterary 192:168.1.14 Printer Network Setting 192:168.1.14 IP Address IP Address IP Address IP Address IP Address IP Address IP Addres	
IP Address 192.168.1.114 Netmask 255.255.255.0 Gateray 192.168.1.1 Printer Network Setting 256.255.255.0 IP Address 192.168.1.114 Netmask 255.255.255.0 Gateray 192.168.1.114 Netmask 192.168.1.114 Setary 192.168.1.114 Printer Parameter Setting 192.168.1.114 Printer Parameter Setting Tata bit< Bolt Network	
Netmaak Gaterary 255 255 0 192 Thirder Network Setting 120 0-80 +el-11-00 192 168 1114 IP Address 192 168 1114 Setter 192 168 1114 IP Address IP Address IP Addr	
Gatewy 192.168.1.1 Printer Network Setting 22-0e-08-e1-11-06 IP Address 192.168.1.114 IP Address 192.168.1.114 Netmaak 255.255.255.0 Gateway 192.168.1.114 Seture 192.168.1.1 Seture Seture Printer Parameter Setting 192.168.1.1 Bask Aric S90.0 Uate bit Bit Bask Aric 192.124 PrintMode 114 Bask Ari	
Printer Vectorials Setting 28-08-06-01-11-06 192-168-11-11-0	
MAC Address 22-0e-8b-el-11-bb IP Address 192:168.11:14 Notmask 255:255:0 Galaxy 192:168.11:14 Statuy 1121 Statuy 1121 Statuy 1121 Statuy 1121 Statuy 1121 Statuy 1121 Statuy 114 Statuy 114 Statuy 114 Statuy 114 Statuy 114 Statuy 114 Statuy	
IP Address 192 168 1.114 Netmask 255 255 255 0 Gaterray 192 168 1.11 Seture 192 168 1.11 Seture 192 168 1.11 Printer Parameter Setting 192 168 1.11 Factory SPRT Model TL21 Setual Number: TL21E2202000001 Top Keep Time(Second) Baod Rate: 5600 v Data bit BBV P antry: None v Handshaking RTS:CTS v Language: Otiniese-BIOS Printfront: 12/22 v PrintNich: 30mm v PrintDensky: Light v PrintSpeed 70mmiS v PrintMode: 展展 V BiackMark: ON v LabiPaperSensor: 1 v PrintDrection: Reverse v Command Set: SPMP v Setup Setup Setup Setup DHCP Enable: OFF v Setup	
Netmaak 255 255 0 Gdeway 192 168 1: Seture 192 168 1: Printer Parameter Setting Frinter Parameter Setting Trop Keep Time(Second) Baud Rate: 9600 v Data bit: Biti v Party: None v Handshakking: RTS/CTS v Language: Chinese-BIGS Pint/Fort: 12/24 v Pint/Nidh: 30mm v Pint/Beakly: Light v Pint/Direction 70mmS v Pint/Node: ### v BiackMark: CP437 v Pint/Parksensor: 1 v Pint/Parksensor Command Set: SPMP v Setup Setup Setup Seture DHCP Enable: OFF v Seture	
Sateway 192 163 1.1 Seture 192 163 1.1 Seture 192 163 1.1 Factory: SPRT Model: TL21 Seture Setial Number: TL21E2202000001 Tcp Keep Time(Second) Baud Rate: S600 Baud Rate: S600 Baud Rate: S600 Dimmon Printpress BlackMark: ON Dim NormalPaperSensor: 1 Baud Rate: ON Dim NormalPaperSensor: 1 BlackMark: ON CodePage: CP437 Seturp Seturp Seturp Seturp Software Update OFF	
IPI INDERIFY Factory: SPRT Model TL21 Serial Number: TL21E2202000001 Tcp Keep Tima[Second] Baud Rate: 9600 Data bit. 8 bit ♥ Parity: None ♥ Handshaking: RTS:CTS ♥ Language: Chinese-BIOS Baud Rate: 9600 Data bit. 8 bit ♥ Parity: None ♥ Handshaking: RTS:CTS ♥ Language: Chinese-BIOS BiadsMark: ON ♥ NormalPaperSensor: 1 ♥ Printerve Printerve OHCP Enable OEF ♥ Software Update Serial Serial Serial Serial OFF ♥ Serial	
Issue Printer Parameter Setting Printer Parameter Setting Factory SPRT Model TL21 Setial Number: TL21E220200001 Top Keep Time(Second) Baud Rate: 6600 v Data bit: Bbit v Party: None v Handshaking: RTS:CTS v Language: Chinese-BI05 Print/font: 12/22 v PrintMidel: 30mm v PrintDansky: Light v PrintSpeed: 70mm S PrintMode R## v Bit##	
Printer Parameter Setting Factory SPRT Model TL21 Serial Number: TL21E220200001 Tcp Keep Time(Second) Baud Rate: 6600 v Data bit: 8 bit v Party: None v Handshaking: RTS:CTS v Language: Chinese-BIOS Print/Font: 12/22 v Print/Model 30mm v Print/Deradlor: Upt v Print/Speed 70mm S Print/Mode ### v BiackMark: ON v Normal/PepeSensor: 1 v Language: Command Set: SPMP v Code/Page: CP437 v PaperOutReprint: ON v USB Class: Printer v DHCP Enable: OFF v	
Factory: SPRT Model TL21 Serial Number: TL216220200001 Tcp Keep Time(Second) Baid Rate: 6600 v Data bit: 8 bit v Party: None v Handshakking: RTS/CTS v Language: Chinese-BIGS Print/Font: 12/24 v Print/Second Print/Second <t< td=""><td></td></t<>	
Baud Rate: 5600 v Data bit: 8 bit v Parity: None v Handshaking: RTS/CTS v Language: Chinese-BIGS Print/Font: 12/24 v Print/Ndhr: 30mm v Print/Densky: Light v Print/Speed: 70mm/S v Print/Ndhr: #### v BlackMark: ON v NormaPapeSensor: 1 v LablePape/Sensor: 1 v Print/Pape/Sensor: 1 v Print/Pape/Sensor: Reverse v Command Set: SPMP v CodePage: CP437 v Paper/OutReprint: ON v USB Class: Printer v DHCP Enable: OFF v Software Update	300
PrintFont: 12/24 v Print/Vidit: 30mm v Print/Jensky: Light v Print/Speed 70mmS v Print/Note: 展示 BlackMark: ON v NormaPaperSensor: 1 v LablePaperSensor: 1 v Print/Paper Command Set: SPMP v CodePage: CP437 v PaperOutReprint: ON v USB Class: Printer v DHOP Enable: OFF v Setup Software Update	~
BlackMark: ON NormalPaperSensor: 1 LablePaperSensor: 1 PrintDirection: Reverse Command Set: SPMP CodePage: CP437 PaperOutReprint: ON USB Class: Printer DHCP Enable OFF Command Set: SPMP SPMP Software Update	
Code/Page: CP437 PaperOutReprint: ON USB Class: Printer DHCP Enable; OFF Setup Software Update Software Update <td></td>	
Setup Software Update	
Software Update	
Inclus	

- 6. 印表機 IP 變更成功後,電腦端請改回原 IP 位址(同步驟 3)。
- 7. 安裝驅動程式後,印表機連接埠位址設定正確,即可測試列印。

府 获重和印度通	- D X
← → ~ ↑ 福 > 控制台 > 所有控制台項目 > 装置和印表機 >	→ ひ 按导 統置和印表機 の
新油装置 新增印表機 查看列印工作 列印间程器内容 移除装置	≅ • 0
~ 印表機 (12)	
Citizen CL-E331 EPSON L655 Series EPSON L6190 Series EPSON/E6190 (L6490 Serier) Fax	KPOS Printer Microsoft Print Microsoft XPS OKI-MC361-32 OneNote Destroy Printer Ver.4.01
() 会議課題(10)	Writer 最 SPRT TL2X Printer 內晋 X
DESKTOP-VSI_L eHomeMediaC USA myTwonky OU enter USA myTwonky Ubrary at VSINAS	 一般 共用 連接準 塗陽 色彩管理 安全性 装置設定 請言 第於 ● SPRT TL2X Printer 列印到下列總接場(P) 文件場會列印到第一個可使用的磁取連接場。
V 装置 (4) POS13 S242HL USB Keyboard USB OPTICAL MOUSE	摄理增 描述 印表描 ^
SPRT TL2X Printer 放振: ●基	□ 飲用印表機集區(N) 確定 取消 家用(A)